Datasheet and description



Avide Design Oyster Arlo 91W(45.5+45.5) with RF Remote

Product code: ADO3S-91W-ARL-2.4G

Brand link: avidelighting.com/qr/ADO3S-91W-ARL-2.4G

ID: AB-190518

Company name: Armin Trade Kft.

Company address: Kossuth utca 22 2/4, 4024 Debrecen



Date of issue: 2022-08-04

Page: 1/3

SPECIFICATIONS

EAN code: 5999097929262

Warranty: 3year(s)

Material: Acryl+Metal

Working temperature: -20 + 40°C

Packaging: 1/b 5/c

Certifications: CE

TECHNICAL DETAILS

Type of LED:

Wattage: 91W

Voltage: 200-265V

Beam angle: 120°

Dimmability: Yes

Lumen output: 6 370lm

Color temperature: 5 000K

Lifetime: 25 000h

SMD2835

CRI: 80
IP standard: IP20

BOX PICTURE



Datasheet and description



Avide Design Oyster Arlo 91W(45.5+45.5) with RF Remote

Product code: ADO3S-91W-ARL-2.4G

Brand link: avidelighting.com/qr/ADO3S-91W-ARL-2.4G

ID: AB-190518

Company name: Armin Trade Kft.

Company address: Kossuth utca 22 2/4, 4024 Debrecen



Date of issue: 2022-08-04

Page: 2/3

PRODUCT SIZE

Diameter: 500mm Height: 73mm

CARDBOARD BOX

EAN: 5999097929262

Packaging: 1/b 5/c

Dimensions: 550mm x 555mm x 100mm

Net weight: 3 120g Gross weight: 3 760g

CARTON

EAN: 5999097929279

Packaging: 1/b 5/c


Dimensions: 570mm x 530mm x 570mm

Net weight: 15.6kg Gross weight: 18.8kg

PRODUCT PICTURE



PRODUCT OUTLINE



PALLET EXAMPLE

Height:

Width: 120cm (std Euro pallet)

Mepth: 80cm (std Euro pallet)

Cartons per pallet: 0carton/pallet

Cartons per row:

Net weight: 3.12kg
Gross weight: 3.76kg

Datasheet and description



Avide Design Oyster Arlo 91W(45.5+45.5) with RF Remote

Product code: ADO3S-91W-ARL-2.4G

Brand link: avidelighting.com/qr/ADO3S-91W-ARL-2.4G

ID: AB-190518

Company name: Armin Trade Kft.

Company address: Kossuth utca 22 2/4, 4024 Debrecen



Date of issue: 2022-08-04

Page: 3/3

PRODUCT DESCRIPTION

The new Avide design oysters bring unique style to our home.

There are 3 lighting modes available for each model. The first and second modes use a combination of warm white and cold white LEDs to achieve different lighting effects, while the third mode uses a combination of warm white and cold white LEDs to create a natural white color temperature, doubling the power and brightness as well.

Before the very first use, the remote controller has to be paired with the lamp!

Pairing: Within 5 seconds of power ON, push the marked (WIFI signed) button once shortly. If the pairing was successful, the lamp will blink 3 times and the remote controller is ready to use.

Unpairing: Within 5 seconds of power ON, push the marked (WIFI signed) button 3 times shortly. If the unpairing was successful, the lamp will blink several times.

In addition to switching between modes, the product's RF remote controller also allows you to adjust the brightness and color temperature, and to activate the timer function: Press once for 5 minutes, press twice for 30 minutes and press three times for turn off the timer.

The product has a memory function, so the previously used mode and brightness will be active at the next time you turn it on.